

ON SOME SPECIAL THETA FUNCTIONS

BY

F. VAN DER BLIJ AND J. H. VAN LINT¹⁾

(Communicated by Prof. H. FREUDENTHAL at the meeting of September 27, 1958)

1. Preliminaries

In this paper we shall use the usual notation $\{ \Gamma, -r, v \}$ for the class of modular forms of dimension $-r$ for the group Γ , with multiplier system v .

$\Gamma[1]$ is the modular group, i.e. the group of integral matrices $\begin{pmatrix} a & b \\ c & d \end{pmatrix}$ with $ad-bc=1$. We use the same notation for the associated group of transformations $\tau \rightarrow \frac{a\tau+b}{c\tau+d}$.

We write:

$$I = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix}, \quad U = \begin{pmatrix} 1 & 1 \\ 0 & 1 \end{pmatrix}, \quad T = \begin{pmatrix} 0 & -1 \\ 1 & 0 \end{pmatrix}.$$

$\Gamma[N]$ is the subgroup of $\Gamma[1]$ defined by $\begin{pmatrix} a & b \\ c & d \end{pmatrix} \equiv \pm I \pmod{N}$.

$\Gamma_0[N]$ and $\Gamma^0[N]$ are the subgroups of $\Gamma[1]$ defined by $c \equiv 0 \pmod{N}$ and $b \equiv 0 \pmod{N}$ respectively.

Γ_θ is the group generated by U^2 and T .

The functions η , ϑ_{gh} and G_k are defined as follows:

$$\eta(\tau) = e^{\frac{\pi i \tau}{12}} \prod_{n=1}^{\infty} (1 - e^{2\pi i n \tau}) \quad (\text{Im } \tau > 0).$$

$$\vartheta_{gh}(\tau) = \sum_{n=-\infty}^{+\infty} (-1)^{nh} e^{\pi i \tau (n + \frac{1}{2}g)^2} \quad (\text{Im } \tau > 0, g \text{ and } h \text{ integers}).$$

$$G_k(\tau) = \frac{1}{2\zeta(k)} \sum'_{m_1, m_2} (m_1 \tau + m_2)^{-k} \quad (\text{Im } \tau > 0, k \text{ even}).$$

If S is the matrix (s_{ij}) we shall write the quadratic form $\sum_{i,j=1}^n s_{ij} x_i x_j$ as $x' S x$.

2. The theta functions

It is well known that the theta functions ϑ_{00} , ϑ_{01} and ϑ_{10} are modular forms for the groups Γ_θ , $\Gamma^0[2]$ and $\Gamma_0[2]$ respectively. These groups are subgroups of index 3 of the full modular group $\Gamma[1]$. From these functions one can form modular forms for the group $\Gamma[1]$. A well known example is the fact that $\vartheta_{01}^{4k} + \vartheta_{10}^{4k} + (-1)^k \vartheta_{00}^{4k} = F_k$ where $F_k \in \{ \Gamma[1], -2k, v \}$. Here v is determined by $v(U) = (-1)^k$.

¹⁾ The preparation of this paper was supported in part by the Netherlands Organisation for Pure Research (Z.W.O.).

We shall now give a more general definition of theta functions and try to construct modular forms for $I[1]$ with these. We consider an integral positive definite quadratic form $x'Sx$ in n variables and two arbitrary vectors a and b and consider the function

$$\sum_{x \equiv a \pmod{1}} e^{\pi i \tau x'Sx} e^{2\pi i x'Sb} \quad (\text{Im } \tau > 0).$$

The factor $e^{\pi i \tau x'Sx}$ enters into the sum when we consider the transformation $\tau \rightarrow \tau + 1$. We introduce a vector w with the property

$$x'Sx \equiv 2x'Sw \pmod{2}$$

for all integral x . It is easily seen that this is possible and that we can take $w=0$ if $x'Sx$ is an even form.

We shall require that S has determinant 1. Then the transformation $\tau \rightarrow \frac{-1}{\tau}$ maps the function into another function of the same type multiplied by a factor which depends on a and b . We now change our definition so that these transformation formulae no longer depend on a and b . In this way we come to the definition

$$(2.1) \quad \vartheta\left(\tau \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right) = e^{-\pi i \{a'Sb + 2a'Sw + w'Sw\}} \sum_{x \equiv a+w \pmod{1}} e^{\pi i \tau x'Sx} e^{2\pi i x'S(b+w)}.$$

The transformation formulae are

$$(2.2) \quad \vartheta\left(\tau \left| \begin{smallmatrix} a+g \\ b+h \end{smallmatrix} \right.\right) = e^{\pi i \{a'Sh - b'Sg\}} (-1)^{g'Sg + h'Sh + g'Sh} \vartheta\left(\tau \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right)$$

for integral vectors g and h .

$$(2.3) \quad \vartheta\left(\tau \left| \begin{smallmatrix} -a \\ -b \end{smallmatrix} \right.\right) = e^{4\pi i w'Sw} \vartheta\left(\tau \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right),$$

$$(2.4) \quad \vartheta\left(\tau + 1 \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right) = e^{\pi i w'Sw} \vartheta\left(\tau \left| \begin{smallmatrix} a \\ a+b \end{smallmatrix} \right.\right),$$

$$(2.5) \quad \vartheta\left(\frac{-1}{\tau} \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right) = \tau^{\frac{n}{2}} e^{-\frac{\pi i n}{4}} e^{-2\pi i w'Sw} \vartheta\left(\tau \left| \begin{smallmatrix} b \\ -a \end{smallmatrix} \right.\right).$$

Using $(UT)^3 = -I$ we find from these relations:

$$\vartheta\left(\tau \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right) = e^{\pi i \left\{ \frac{n}{4} - w'Sw \right\}} \vartheta\left(\tau \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right).$$

As S is positive definite we have $\vartheta\left(\tau \left| \begin{smallmatrix} -w \\ -w \end{smallmatrix} \right.\right) \neq 0$ and hence $\frac{n}{4} \equiv w'Sw \pmod{2}$. If S is an even form we find the condition $n \equiv 0 \pmod{8}$ (cf. [1]).

In some cases it is easier to work with modular functions than modular forms. We therefore define

$$(2.6) \quad \varphi\left(\tau \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right) = \vartheta\left(\tau \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right) \cdot \eta^{-n}(\tau).$$

We have:

$$(2.7) \quad \varphi\left(\tau+1 \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right) = e^{\frac{\pi i n}{6}} \varphi\left(\tau \left| \begin{smallmatrix} a \\ a+b \end{smallmatrix} \right.\right),$$

$$(2.8) \quad \varphi\left(\frac{-1}{\tau} \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right) = e^{-\frac{\pi i n}{2}} \varphi\left(\tau \left| \begin{smallmatrix} b \\ -a \end{smallmatrix} \right.\right).$$

From (2.7) and (2.8) we find for $L = \begin{pmatrix} \alpha & \beta \\ \gamma & \delta \end{pmatrix} \in \Gamma[1]$ the transformation formula

$$(2.9) \quad \varphi\left(L\tau \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right) = \varepsilon(L) \cdot \varphi\left(\tau \left| \begin{smallmatrix} \alpha a + \gamma b \\ \beta a + \delta b \end{smallmatrix} \right.\right).$$

Here $\varepsilon(L)$ is a character of the group $\Gamma[1]$. If we write $\xi = e^{\frac{\pi i n}{6}}$ we have (cf. [2])

$$(2.10) \quad \varepsilon(L) = \begin{cases} \xi^{(\alpha+\delta)\gamma - \beta\delta(\gamma^2-1) - 3\gamma} & \text{if } \gamma \equiv 1 \pmod{2}, \\ \xi^{(\alpha+\delta)\gamma - \beta\delta(\gamma^2-1) + 3\delta - 3 - 3\gamma\delta} & \text{if } \delta \equiv 1 \pmod{2}. \end{cases}$$

We shall now restrict ourselves to the case where there is an integer N such that Na and Nb are integral vectors. Then, by (2.9) and (2.2), we have, if $L \equiv \pm I \pmod{N}$:

$$(2.11) \quad \varphi\left(L\tau \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right) = \varepsilon(L) \varrho(L, a, b) \varphi\left(\tau \left| \begin{smallmatrix} a \\ b \end{smallmatrix} \right.\right).$$

Hence φ is a modular function of $\{I[N], 0, \varepsilon\varrho\}$.

Here $\varrho(L, a, b)$ is a root of unity which depends on L , a and b in a complicated way. We introduce the following notation:

$$A = N^2 a' S a, \quad B = N^2 b' S b, \quad \text{and} \quad C = 2N^2 a' S b.$$

We take $L \equiv I \pmod{N}$, and write:

$$L = \begin{pmatrix} \alpha & \beta \\ \gamma & \delta \end{pmatrix} = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} + N \begin{pmatrix} \alpha' & \beta' \\ \gamma' & \delta' \end{pmatrix}.$$

Then we find:

$$(2.12) \quad \varrho = e^{\frac{\pi i}{N}(\beta' A + \delta' C - \gamma' B)} (-1)^{(\alpha' + \alpha' \beta' + \beta' A) + (\gamma' + \gamma' \delta' + \delta' B)}.$$

If N is odd this reduces to

$$\varrho = e^{\frac{\pi i}{N} \frac{N+1}{2} (\beta' A - \gamma' B)} e^{\frac{\pi i}{N} \frac{\delta' C}{2}}.$$

3. Relations for the theta functions

We wish to find linear combinations of the functions φ which are a modular function for $\Gamma[1]$. It is clear that we can restrict the a and b to vectors of a lattice generated by two given vectors a_0 and b_0 . Now if the function of $\Gamma[1]$ is not identically zero it generally must have the form $\varphi|T[K, A]$ where $T[K, A]$ is a general Hecke-operator introduced by WOHLFAHRT ([3]). From the theory of these we see that a necessary condition is that there is a character of $\Gamma[1]$ which is equal to $\varepsilon\varrho$ on the subgroup $\Gamma[N]$. In this way we find restrictions for the vectors a and b

that are to be used. We shall distinguish different values of N and give some necessary conditions for the existence of linear combinations which belong to $I[1]$.

The value of the character for U^N must be $\varepsilon(U^N)\varrho(U^N, a, b)$. This gives us the condition

$$nN^2 + 6A(N+1) \equiv 0 \pmod{\{2N \cdot (6, N)\}}.$$

We distinguish

1) $N \equiv 1 \pmod{2}$.

Then the above condition is equivalent with $n \equiv 0 \pmod{2}$ and $A \equiv 0 \pmod{N}$. Using $\begin{pmatrix} 1 & 0 \\ N & 1 \end{pmatrix}$ and $\begin{pmatrix} 1+N & N \\ N & 1-N \end{pmatrix}$ we find in the same way: $B \equiv 0 \pmod{N}$ and $C \equiv 0 \pmod{2N}$. In this case $\varrho = 1$.

2) $N \equiv 0 \pmod{4}$ or $N \equiv 2 \pmod{4}$ and $n \equiv 0 \pmod{2}$.

In the same way as above we find $A \equiv B \equiv C \equiv 0 \pmod{2N}$ and $\varrho = 1$.

3) $N \equiv 2 \pmod{4}$ and $n \equiv 1 \pmod{2}$.

We find $A \equiv B \equiv C \equiv N \pmod{2N}$ and $\varrho = (-1)^{\beta' + \delta' - \gamma'}$.

In some cases there are different characters of $I[1]$ which are equal to $\varepsilon\varrho$ on $I[N]$. To get linear combinations of the functions φ which are not identically zero and belong to $I[1]$ we must consider a function φ and the largest subgroup of $I[1]$ for which it is a modular function and then find a character of $I[1]$ which has the same value on this subgroup. Even then we can sometimes find two or more such characters. In 4 we shall give an example of this case.

4. Examples

We shall give some examples of the relations one can find for the functions φ . We consider three different cases, namely

1) $a=b=0$, 2) $a=0$, b arbitrary, and 3) a and b linearly independent.

4.1. $a=b=0$. In this case $\varphi(\tau) = \varphi\left(\tau \middle| \begin{smallmatrix} 0 \\ 0 \end{smallmatrix}\right)$ is already a modular function for the group $I[1]$. From (2.3) we see that $\vartheta\left(\tau \middle| \begin{smallmatrix} 0 \\ 0 \end{smallmatrix}\right) = (-1)^{n\vartheta}\left(\tau \middle| \begin{smallmatrix} 0 \\ 0 \end{smallmatrix}\right)$ and hence if $\varphi \neq 0$, n must be even. In fact if $n \leq 11$ we have $\vartheta\left(\tau \middle| \begin{smallmatrix} 0 \\ 0 \end{smallmatrix}\right) = 0$, except if $n=8$ and S is an even form.

For $n=12$ and $x'Sx = 23x_1^2 + 2 \sum_{i=2}^{12} x_i^2 + 10x_1x_2 + 2 \sum_{i=2}^{11} x_i x_{i+1}$ we have

$$\vartheta\left(\tau \middle| \begin{smallmatrix} 0 \\ 0 \end{smallmatrix}\right) = - \sum_{x \equiv (0, i, 0, i, \dots, 0, i) \pmod{1}} e^{\pi i x x' S x} e^{\pi i x_1} = 24\eta^{12}(\tau) \text{ (cf. [4])}.$$

4.2. $a=0$. In this case the functions φ are modular functions for the group generated by U and $I[N]$. If $N=2$ we have

$$\varphi\left(\tau \middle| \begin{smallmatrix} 0 \\ b \end{smallmatrix}\right) + \varphi\left(\tau \middle| \begin{smallmatrix} b \\ 0 \end{smallmatrix}\right) + \varphi\left(\tau \middle| \begin{smallmatrix} b \\ b \end{smallmatrix}\right) = \Phi(\tau) \text{ with } \Phi \in \{I[1], 0, v\}.$$

Here a necessary condition is that $b'Sb$ is an integer. As example we take for S the unit matrix. If one of the components of b is 0 we have $\varphi=0$. Therefore we can assume that all components of b are $\frac{1}{2}$. Then $n \equiv 0 \pmod{4}$.

After multiplying by η^{4k} the relation becomes

$$(4.1) \quad \vartheta_{01}^{4k} + \vartheta_{10}^{4k} + (-1)^k \vartheta_{00}^{4k} = F_k \varepsilon \{ \Gamma[1], -2k, v \}.$$

We have: $F_1 = 0$; $F_2 = 2G_4$; $F_3 = -48\eta^{12}$; $F_4 = 2G_8$.

This is a well known result.

If $N=3$ we have

$$\varphi\left(\tau \middle| \begin{smallmatrix} 0 \\ b \end{smallmatrix}\right) + \varphi\left(\tau \middle| \begin{smallmatrix} b \\ 0 \end{smallmatrix}\right) + \varphi\left(\tau \middle| \begin{smallmatrix} b \\ b \end{smallmatrix}\right) + \varphi\left(\tau \middle| \begin{smallmatrix} -b \\ b \end{smallmatrix}\right) = \Phi(\tau) \text{ with } \Phi \in \{ \Gamma[1], 0, v \}.$$

Here a necessary condition is that $b'Sb \equiv 0 \pmod{3}$ and $n \equiv 0 \pmod{2}$. If we take as S the unit matrix we again have $\varphi=0$ if one of the components of $b=0$. It is easily seen that we can therefore restrict ourselves to vectors b with all components equal to $\frac{1}{2}$. Then we have $n \equiv 0 \pmod{6}$ and as

$$\sum_{x \equiv \frac{1}{2} \pmod{1}} e^{\pi i \tau x^2} e^{2\pi i \frac{1}{6} x} = -\sqrt{3} \eta(3\tau)$$

we find a relation which can be written as

$$(4.2) \quad \eta^{6k} | T(3) \in \{ \Gamma[1], -3k, v \},$$

where $T(3)$ is a generalized Hecke-operator (cf. [3]).

For $k=1$ we have $\eta^6 | T(3) = 0$, for $k=2$: $\eta^{12}(\tau) | T(3) = c \cdot \eta^{12}(\tau)$.

Finally we give an example with $N=5$, $n=2$. Let S be the unit matrix and $a=0$, $b = \frac{1}{5}(1, 2)$. Then

$$\begin{aligned} \vartheta\left(\tau \middle| \begin{smallmatrix} a \\ b \end{smallmatrix}\right) &= -i \left\{ \sum_{x \equiv \frac{1}{5}(1)} e^{\pi i \tau x^2} e^{2\pi i \frac{1}{10} x} \right\} \left\{ \sum_{x \equiv \frac{1}{5}(1)} e^{\pi i \tau x^2} e^{2\pi i \frac{2}{10} x} \right\} = \\ &= -4i \left\{ \sum_{n=0}^{\infty} e^{\frac{\pi i \tau (2n+1)^2}{4}} \cos \frac{3(2n+1)\pi}{10} \right\} \left\{ \sum_{n=0}^{\infty} e^{\frac{\pi i \tau (2n+1)^2}{4}} \cos \frac{(2n+1)\pi}{10} \right\} \end{aligned}$$

$$\text{and } \varphi(\tau) = \frac{\vartheta\left(\tau \middle| \begin{smallmatrix} a \\ b \end{smallmatrix}\right)}{\eta^2(\tau)}.$$

$\varphi \in \{ \Gamma_0[5], 0, v \}$ where v is a character of $\Gamma[1]$. The relation is

$$\vartheta\left(\tau \middle| \begin{smallmatrix} 0 \\ b \end{smallmatrix}\right) + \vartheta\left(\tau \middle| \begin{smallmatrix} b \\ b \end{smallmatrix}\right) + \vartheta\left(\tau \middle| \begin{smallmatrix} 2b \\ b \end{smallmatrix}\right) + \vartheta\left(\tau \middle| \begin{smallmatrix} 3b \\ b \end{smallmatrix}\right) + \vartheta\left(\tau \middle| \begin{smallmatrix} 4b \\ b \end{smallmatrix}\right) + \vartheta\left(\tau \middle| \begin{smallmatrix} b \\ 0 \end{smallmatrix}\right) = 0.$$

4.3. a and b independent.

In all the examples S will be the unit matrix.

i) $N=2$, $n=3$, $a = (\frac{1}{2}, \frac{1}{2}, 0)$, $b = (0, \frac{1}{2}, \frac{1}{2})$.

$\vartheta\left(\tau \middle| \begin{smallmatrix} a \\ b \end{smallmatrix}\right) = -\vartheta_{00}(\tau) \vartheta_{01}(\tau) \vartheta_{10}(\tau) = -2\eta^3(\tau)$. Hence $\varphi=2$ which is a trivial modular function for $\Gamma[1]$.

ii) $N=2$, $n=8$, $a = (\frac{1}{2}, \frac{1}{2}, \frac{1}{2}, \frac{1}{2}, 0, 0, 0, 0)$, $b = (0, 0, 0, 0, \frac{1}{2}, \frac{1}{2}, \frac{1}{2}, \frac{1}{2})$.

Then the theta function is $\vartheta_{01}^4 \vartheta_{10}^4 \in \{ \Gamma_\theta, -4, v \}$.

The relation we find is

$$(4.3) \quad -\vartheta_{01}^4 \vartheta_{10}^4 + \vartheta_{00}^4 \vartheta_{10}^4 + \vartheta_{00}^4 \vartheta_{01}^4 = G_4.$$

This can be derived from (4.1).

iii) $N=2$, $n=15$, $a=\frac{1}{2}(0, 1, \dots, 1)$, $b=\frac{1}{2}(1, 1, 1, 1, 1, 1, 0, \dots, 0)$.

The theta function is $-\vartheta_{10} \vartheta_{00}^5 \vartheta_{01}^9 \in \left\{ \Gamma[2], -\frac{15}{2}, v \right\}$. In this case there are two characters of $\Gamma[1]$ which are equal to the multiplier of φ on $\Gamma[2]$. Therefore we find two operators mapping φ into a modular function of $\Gamma[1]$. The two relations can be written as follows:

$$\begin{aligned} \text{Define } F &= -\vartheta_{00}^4 \vartheta_{01}^8 + \vartheta_{10}^4 \vartheta_{00}^8 + \vartheta_{01}^4 \vartheta_{10}^8 \\ G &= \vartheta_{01}^4 \vartheta_{00}^8 - \vartheta_{00}^4 \vartheta_{10}^8 + \vartheta_{10}^4 \vartheta_{01}^8. \end{aligned}$$

Then F and G are modular forms of $\{\Gamma, -6, 1\}$ where Γ is the subgroup of index 2 of $\Gamma[1]$ generated by U^2 and UT .

We have

$$(4.4) \quad \begin{cases} F+G=48 \eta^{12} \\ F-G=-2 G_6. \end{cases}$$

iv) $N=3$, $n=6$, $a=\frac{1}{3}(0, 0, 0, 1, 1, 1)$, $b=\frac{1}{3}(1, 1, 1, 0, 0, 0)$.

$$\text{Then } \vartheta\left(\tau \middle| \begin{smallmatrix} a \\ b \end{smallmatrix}\right) = e^{\frac{\pi i}{3}} \sqrt{3} \eta^3(3\tau) \eta^3\left(\frac{\tau}{3}\right).$$

In this case φ is mapped into 0 by the operator and the relation we find can be written as $\eta^6|T(3)=0$.

*Mathematical Institute
University of Utrecht*

REFERENCES

1. HECKE, E., Analytische arithmetik der positiven quadratischen Formen. Det. Kgl. Danske Vidensk. Selskab, Mat. fys. Medd. XVII, 12.
2. PETERSSON, H., Über Modulfunktionen und Partitionenprobleme, Abh. d. Deutschen Ak. d. Wiss. Berlin, 2 (1954).
3. WOHLFAHRT, K., Über Operatoren Heckscher Art bei Modulformen reeller Dimension, Math. Nachr. Bd. 16 (1957).
4. CHAO KO, On the positive definite quadratic forms with determinant unity, Acta Arithmetica Bd. 3 (1939).